



## FOX "FOX"



For illustrative purposes only

### ENGINE

Description	PERKINS
Engine model	404J-22G
Cylinders	4
RPM speed	1500
Cubic capacity	2.22 l
Air intake	Aspirated
Standard voltage	12 Vdc
Optional voltage	Vdc
Sae	4-7
BMEP	671 kPa
Cooling	Water
Flywheel P.R.P. Power net	18.5 kW
Flywheel Stand-by Power net	20.5 kW
Fuel Cons. at 100% (E.P.)	6.4 l/h
Fuel Cons. at 100% (P.R.P.)	5.6 l/h
Fuel Cons. at 75% (P.R.P.)	4.0 l/h
Fuel Cons. at 50% (P.R.P.)	2.2 l/h
Fuel Cons. at 25% (P.R.P.)	0.0 l/h
Electronic regulator	Not available
Precision class	
Oil quantity	10.6 l
Engine Antifreeze capacity	3.6 l
Radiator type	TR
Heat from radiator	15.2 kW
Heat from exhaust	12.6 kW
Heat from radiation	2.9 kW
Exhaust temperature	490 °C
Portata Raffreddamento	60.0 m <sup>3</sup> /min
Combustion air flow	2.0 m <sup>3</sup> /min
Exhaust gas flow	3.6 m <sup>3</sup> /min
TA Luft	N
TA Luft/2	N
EPA	N
Stage	5

### MAIN DATA

Continuous power (PRP)	<b>20.00</b> kVA
Continuous power (PRP)	<b>16.00</b> kW
Emergency power (E.P.)	<b>22.00</b> kVA
Emergency power (E.P.)	<b>17.60</b> kW
VAC - HZ - cos(fi)	<b>415 - 50 - 0.8</b>
Sound pressure 7 m.	<b>65</b> dBA

### DIMENSIONS AND WEIGHT

Width	770 mm
Length	1660 mm
Height	1330 mm
Weight	680 kg

### ALTERNATOR

Description	STAMFORD
Alternator model	S0L2-G
P.R.P. Power	20 kVA
E.P. Power	22 kVA
Connection	Series star
Phases	3FN
Winding	311
Terminal Number	12 nr.
IP Protection	23
Electronic regulator	AS540
Precision	1 ± %

### BASEFRAME

Model	FOX
Standard tank	50 l
Optional tank	600 l
Oversized tank*	0 l

### CANOPY & SILENCER

Canopy model	FOX
Silencer model	F50/02
Silencer outlet diameter	50 mm

Standard reference conditions temperature 25°C, altitude 100m asl, relative humidity 30%, atmospheric pressure 100 kPa (1 bar), power factor 0.8 lag, balanced load - non distortional. Fuel consumption is nominal and refers to specific weight 0.850kg/l. Sound power values refer to free field conditions: the installation site may influence the values. Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nominal, subject to tolerances and refer to the model with standard equipment; any optional and additional equipment/accessories can modify weight, dimensions, performance. **P.R.P. - Prime Power-Continuous power at variable load:** The power that a genset can supply in continuous service at a variable load for an unlimited number of hours per year while respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer, according to ISO8528-1. The average power supplied over time and any applicable overload must be less than the percentages stated by the Manufacturer. **E.P. - Emergency power:** This is the maximum power that a generating set can deliver for a limited number of hours per year while complying with the maintenance frequency stipulated under the environmental conditions set by the Manufacturer. The number of hours per year is determined by the engine manufacturer. The average power output over time must be lower than the percentages set by the engine manufacturer. Overloading is not allowed.

The data contained in this document is nominal and refers to the standard equipped model and is not binding. Visa S.p.A. reserves the right to revise the information without notice per our policy of continuous product development and improvement.

